

## 24BIT SWITCH REGISTER



### 《ABSTRACT》

- ◆ This module sends 24bit data selected by 24 switches to computer through CAMAC DATAWAY, captures 24bit data specified by computer and display its bit informations using LED.
- ◆ It can do the CAMAC DATAWAY test and the test of Branch highway, Branch driver and computer interface etc.
- ◆ This module can be used for the specification of memory location or the starting of data label and specified program in various physical experiment and measurement.

### 《Specifications》

CAMAC function ia as follows.

N•F(0)A(0) : the reading of written data.

N•F(0)A(1) : the reading of switch data.

N•F(8)A(0) : LAM test

N•F(10)A(0) : LAM clear

N•F(16)A(0) : write data

N•F(24)A(0) : LAM Disable.

N•F(26)A(0) : Enable.

Z•C : Disable LAM register,clear the register for data writing.

- \* It is prepared the function to clear the LAM register. by connecting internal jumper wire,after F(0) data is read,

- ◆ Packaging : CAMAC standard double-width module.
- ◆ Consumption current : +6V Approx.320mA



KAIZUWORKS CORPORATION  
 9-18 HIGASHIMATSUBARA HAKONEGASAKI MIZUHOMACHI  
 NISHITAMAGUN TOKYO 190-1222 JAPAN  
 Tel : 042-568-0866 Fax : 042-568-0867

E-mail [kaizuwks@kaizuworks.co.jp](mailto:kaizuwks@kaizuworks.co.jp) Homepage <http://www.kaizuworks.co.jp>