

DUAL PROGRAMMABLE ATTENUATOR



«ABSTRACT»

- ◆ This module can be set the value from 0.5dB to 31.5dB arbitrarily.
The setting can be done by manual or CAMAC function.
- ◆ The attenuator device is used T type and π type device which is developed specifically.
The impedance is 50 Ω .

«Specifications»

- ◆ CAMAC function is as follows.
 - N•F(0)A(0) : Reads the contents of the Relay position Register.
 - N•F(8)A(0) : Tests the State of the L-source.
 - N•F(10)A(0) : Sets L to Zero.
 - N•F(16)A(0) : Write the Relay position Register.
 - N•F(24)A(0) : Disable the L-source.
 - N•F(26)A(0) : Enable the L-source.
- ◆ The input and output connector : Standard LEMO connector.
- ◆ Packaging : CAMAC standard single-width module.
- ◆ Consumption current : +6V Approx.480mA
 +24V Approx.230mA



KAIZUWORKS CORPORATION
 9-18 HIGASHIMATSUBARA HAKONEGASAKI MIZUHOMECHI
 NISHITAMAGUN TOKYO 190-1222 JAPAN
 Tel : 042-568-0866 Fax : 042-568-0867

E-mail kaizuwks@kaizuworks.co.jp Homepage <http://www.kaizuworks.co.jp>